

# SB72 EX

## 2-Port Serial to Ethernet Server

100 Version



# DATASHEET

### Key Points

- Serial to Ethernet server
- RS-232 and RS-422/485 serial device support
- Works out of the box - no programming is required
- Metal enclosure
- Rebrand with your custom product label
- Customize with development kit

### Features

- 10/100Mbps Ethernet
- TCP/UDP/Telnet modes
- DHCP/Static IP modes
- Web based configuration
- 32-bit performance

### Optional

*The following options are available with the optional development kit:*

- Customize any aspect of operation including web pages, data filtering, or custom network applications
- Additional baud rates available

*The following optional software modules not included with kit and are sold separately:*

- SNMP



## Factory Application Specifications

### Serial Port Baud Rate

Factory application supports up to 115,200 baud. Higher baud rates are available with development kit, but require custom programming.

### Serial Protocols Supported

RS-232, RS-422, and RS-485

### Serial Configurations

The two UARTs can be configured in the following ways:

- Two RS-232 ports
- One RS-232 port, one RS-485/422 port

## Hardware Specifications

### Processor and Memory

32-bit Freescale ColdFire 5272 running at 62.5MHz with 2MB of flash and 8MB of SDRAM.

### Network Interface

10/100 BaseT RJ-45 connector

### Data I/O Interface

- Two UARTs

### LEDs

Link, speed/data, power

### Physical Characteristics

Dimensions (inches): 4.20" x 3.25" x 1.00"

### Power

Power Input: 7-24 VDC

Power Consumption:   Typical 2W  
                                  Max 3W

Weight: 6.1 oz

### Environmental Operating Temperature

0° to 70° C

### RoHS Compliance

The Restriction of Hazardous Substances guidelines ensure that electronics are manufactured with fewer environment harming materials.

### Agency Approvals

UL, C/UL, CE, FCC



## Connector Interface Description and Pinouts

Table 1: Serial Port Connector (Port 0) Pinout and Signal Description<sup>1</sup>

Pin	RS-232 Function	RS-485 Function	Description	Max Voltage
1	CD	-	Carrier Detect	RS-232
2	RX	FD TX- / HD-	Receive or Full Duplex Transmit- / Half Duplex-	RS-232 or RS-422/485
3	TX	FD TX+ / HD+	Transmit or Full Duplex Transmit+ / Half Duplex+	RS-232 or RS-422/485
4	DTR	-	Data Terminal Ready	RS-232
5	GND	GND	Ground	-
6	DSR	FD RX-	Data Set Ready or Full Duplex Receive-	RS-232 or RS-422/485
7	RTS	FD RX+	Ready to Send or Full Duplex+	RS-232 or RS-422/485
8	CTS	-	Clear to Send	RS-232
9	RI	-	Ring Indicator	RS-232

**Note:**

1. Port 0 can be configured to as RS-232 or RS-485

Table 2: Serial Port Connector (Port 1) Pinout and Signal Description

Pin	Port 1 RS-232	Description	Max Voltage
1	CD	Carrier Detect	RS-232
2	RX	Receive	RS-232
3	TX	Transmit	RS-232
4	DTR	Data Terminal Ready	RS-232
5	GND	Ground	-
6	DSR	Data Set Ready	RS-232
7	RTS	Ready to Send	RS-232
8	CTS	Clear to Send	RS-232
9	RI	Ring Indicator	RS-232

## Part Numbers

### **SB72 EX 2-Port Serial to Ethernet Server**

Part Number: SB72-EX-100CR

### **DIN Rail Mounting Kit (100 Version, double sided)**

Part Number: DIN-100

### **DIN Rail Mounting Kit (200 Version, single sided)**

Part Number: DIN-200

### **SB72 EX Development Kit**

Part Number: NNDK-SB72EX-KIT

Kit includes all the hardware and software you need to customize the included platform hardware. See NetBurner Store product page for package contents.

### **SNMP V1 (Module License Version)**

Part Number: NBLIC-SNMP

Available as an option if you are using a development kit.

## Ordering Information

E-mail: [sales@netburner.com](mailto:sales@netburner.com)

Online Store: [www.NetBurner.com](http://www.NetBurner.com)

Telephone: 1-800-695-6828